



Designed rugged and hardened for military operations

Broadcasts intelligible and distorsion free voice communication

Amplified for high noise environments

## **Military Applications**

Designed for use with various radio communication systems used in high noise environments.

## Off / On Volume Control

Built-in rotary volume control, with "audio out off" position.

### Radio Interface

The CJ-PLS-688 loudspeaker is designed to interface with most military radios communication systems used in ground, airborne and sea platforms.

# Amplified for Listening Capability in High Noise

The CJ-PLS-688 is amplified, allowing clear sound in noisy environments such as vehicle systems, field communication shelters, command posts, patrol boats and air troop transport.

## Speaker

Impedance: 8 kOhm between 400 and 4000 Hz

Output: 2 Watts Power: 12-32 vDC Distorsion: < 5 %

Sensitivity: 95 dB @ 1 KHz @ 2.82 vAC

Dimension:

Connector: M55116/2

### **Custom Modifications**

Colors available: CARC, Olive Drab, Desert Tan

# CJ-PLS-688 Loudspeaker

